SHOW DESIGNER 3





Take full control with the new Show Designer 3...

This advanced lighting board is based on the successful and easy-to-use Elation Professional Show Designer 1 & 2. The Show Designer 3 expands on the existing features and adds several others. The approach of this controller is to try to simplify the programming process as much as possible while still offering a high level of control at an affordable cost. This full size universal DMX controller offers you both power and flexibility for all your programming applications. The Show Designer 3 makes programming simple and fast. A Compact Flash drive makes backing up programs, adding fixture profiles and software updates a snap. The latest fixture profiles can be downloaded off the Elation Professional website. Experience the power and take control with Show Designer 3 today!

Show Designer 3 Specifications:





MAIN CONTROL FEATURES

- .1536 DMX Channels
- .3 DMX Universe, 3 & 5 Pin connectors on each output .Control 48 moving light fixtures up to 32 channels each
- .Control 128 Conventional dimmers
- .Playback scenes using buttons or playback faders
- .Effect generator to create chase effects
- .Conventional dimmers can be included in scene memory or be independent.
- .Factory ready color, gobo, focus & effect presets
- .Large moving light fixture library available (same profiles as Show Designer 2)
- .Scene preview with "Go" button
- .Solo feature allows scenes to track through or play solo .Scenes can be combined and recorded as new scenes .Scenes, shows, chases and presets can be assigned to
- the playbacks.

 Playbacks can manually fade channels (LTP mode) or trigger timed fades while manually controlling dimmer levels (HTP mode)

FRONT PANEL

- .80 Character backlit display for easy programming
- .4 menu and control data wheels
- .48 Multi function Quick access buttons
- .100mm faders
- .8 dedicated playback faders with 32 pages
- .8 flex faders with page selection for moving light channels, conventional dimmers or additional playbacks.
- .Pan/tilt joystick with coarse/fine control
- .Grand master fader
- .Flex master fader
- .Go, stop and back buttons
- .Blackout, audio and beat buttons
- .2 USB LITE connectors (for gooseneck lamps)

with EVOLUTION comes CHANGE

SHOW DESIGNER 3 ADVANTAGES:

- .Easy-to-use operation
- .Large moving light fixture library available
- .Software updates available at www.elationlighting.com
- .Compact Flash drive on rear for memory back-up,
- loading fixture profiles and software updates





REAR PANEL CONNECTIONS

- .3 (3 Pin) DMX Outputs
- .3 (5 Pin) DMX Outputs
- .Midi-In port
- .CF-drive for memory back up, loading fixture profiles
- and software updates.
- .PS2 Keyboard input
- .RS-232 Port, for PC interface
- .RCA Audio input for Chases
- Voltage selection switch

CAPACITY

- .4752 programmable scenes
- .1152 programmable chases
- .1152 programmable shows
- .1152 programmable presets
- .48 fixture groups
- .Fade times up to 90 minutes
- .Run 16 chases simultaneously
- Run 17 shows simultaneously

MECHANICAL

.Dimensions: 28" x 23" x 7 / 711 x 584 x 178mm

.Weight: 37 lbs. / 17 kgs.

.110/220V AC power supply

OPTIONAL ACCESSORIES

.SD3RC – Road case .USB LITE (LED gooseneck lamp)



