



## ELAR-Driver-1

### ► DESCRIPTION

ELAR-Driver-1 is a multi-functional LED driver designed to control R.G.B. LEDs.

### ► FEATURES

- 3 channel, RGB LED driver allows for independent channel control
- 6A per channel output capacity
- DMX512 (1990) input & output
- Dip switches for addressing and manual mode operation
- Compact design
- 12~24VDC power requirement

### ► SPECIFICATION

<b>POWER REQUIREMENT</b>	12~24VDC, 6.5A Max.
<b>INPUT</b>	2-pin terminal socket for (DC power) 3-pin terminal socket for (DMX in)
<b>OUTPUT</b>	3-pin terminal socket for (DMX out) 4-pin terminal socket, load max, 6A
<b>HOUSING</b>	Sheet metal black powder coat finish
<b>INGRESS PROTECTION RATING</b>	IP20
<b>CONTROL</b>	DMX-512 (1990)
<b>CONNECTION</b>	Terminal type
<b>LISTING</b>	CE certified
<b>OPERATION TEMPERATURE</b>	0 degC to +40 degC
<b>STORAGE TEMPERATURE</b>	-20 degC to +70 degC
<b>DIMENSION</b>	2.64" x 1.57" x .59" (LxWxH) (67 x 40 x 15mm)
<b>WEIGHT</b>	1lb. (150g)

### ► ORDER CODE

26-007-0259-00	ELAR-Driver-1
----------------	---------------

### ► DIMENSION

